

Model Information



■ Features

- 1 x RS232/422/485 port
- USB 2.0 Full Speed interface
- USB and serial ports ESD protected
- Robust metal case
- Jumperless, DIP ports configuration
- Serial speed max. 1000(RS232) / 3000(RS485) kbps
- DIN-Rail and Wall mount options
- Bus powered, no external power supply
- Wide range operating temperature (-25°C - +75°C)
- slim case

[Contact Online...](#)

USB-COM Plus Mini (USB-COMi-M)

Quick Link: | [Features](#) | [More Pictures](#) | [Overview](#) | [USB Interface](#) | [Serial Interface](#) | [Software](#) | [Power and Environment](#) | [Standards](#) | [Ordering Information](#) | [Options](#) | [Packaging](#) |

■ More Pictures



Click on the thumbnails for the large picture ...

[>Back to top](#)

■ Overview

The modern USB-COM Plus Mini adapter connects one RS232 or RS422/485 device to your PC by a USB 2.0 Full Speed port. The serial port and USB are ESD protected, compliant to IEC 61000-4-2 (8kV contact/16kV air discharges).

The serial port supports RS232, RS422 and RS485 in Full-/Half-Duplex operation mode. The operation mode of the serial port is easy configured by one DIP switch. The configuration also activates built-in RS485 termination if required, no jumpers needed. Standard Drivers are available for all major operating systems.

The USB 2.0 Full-Speed enables serial data rates of up to 3Mbps in RS422/485 or 1000kbps in RS232 modes. The device also allows every non-standard bitrate up to 960 kbps.

The USB-COM Plus Mini is an alternative to the VScom USB-COMi-M.

All USB-COM Plus devices can be used to expand the serial ports for [NetCom Plus Device Servers](#).

■ USB Interface

USB-Input	USB 2.0 Full Speed, USB 1.1 compliant
Connector	USB type B
Protection	Compliant with IEC 61000-4-2 ESD 8kV contact / 16kV air discharge

■ Serial Interface

Port	<ul style="list-style-type: none">• 1 x RS232/422/485 configured by DIP switch• RS485 Termination configured by DIP switch• Polarization/BIAS not required• Connector DSub-9 male
Speed	<ul style="list-style-type: none">• RS232: 180bps - 921.6/1000kbps• RS422: up to 3Mbps• RS485: up to 3Mbps
Available Modes	<ul style="list-style-type: none">• RS232 full duplex• RS422 full duplex• RS485 4-wire, full duplex• RS485 2-wire, half duplex (bus-mode)
Signals	<ul style="list-style-type: none">• RS232: TxD, RxD, RTS, CTS, DTR, DSR, DCD, RI, GND• RS422: Tx+/-, Rx+/-, GND• RS485 4-wire: Tx+/-, Rx+/-, GND• RS485 2-wire: Data+/-, GND
Protection	Compliant with IEC 61000-4-2 ESD 8kV contact / 16kV air discharge
Configuration	One DIP switch defines operation mode and RS422/485 termination

[>Back to top](#)

■ Software

Driver	<ul style="list-style-type: none">• Windows 2000 to Windows 10 (x86 and x64)• Windows Server 2000 to 2012 (x86 and x64)• Linux (Kernel 2.6 and later built-in)• Mac OS X <p>Installation by automatic download from the Internet</p>
---------------	---

[>Back to top](#)

■ Power and Environment

Connector	USB bus powered, no external supply
Protection	Compliant with IEC 61000-4-2 ESD 8kV contact / 16kV air discharge
Dimension	50×72×22 mm ³ (W×L×H) Case 72×72×22 mm ³ (W×L×H) with mounting wings
Operating Temp	-25°C - 75°C
Storage Temp	-30°C - 85°C
Case	SECC sheet metal (0.8mm)
Weight	150g
Mounting	<ul style="list-style-type: none">• DIN-Rail (optional)• Wall mount (optional)
LEDs	LEDs for Power, serial Tx, Rx

[>Back to top](#)

■ Standards

Declarations	CE, FCC
EMI	<ul style="list-style-type: none">• EN 55022 Class B• 47 CFR FCC Part 15 Subpart B
EMS (EN 55024)	<ul style="list-style-type: none">• EN 61000-4-3: Radiated RFI• EN 61000-4-4: Electrical Fast Transient• EN 61000-4-5: Surge• EN 61000-4-6: Induced RFI• EN 61000-4-8: Power Frequency Magnetic Field• EN 61000-4-11: Power supply dips
ESD	EN 61000-4-2 4kV contact 8kV air for <ul style="list-style-type: none">• Serial Port• USB

[>Back to top](#)

■ Ordering Information

655	USB-COM Plus Mini (1x RS232/422/485, non-isolated)
656	USB-COM Plus Mini ISO (1x RS232/422/485, isolated)

[>Back to top](#)

■ Options

<u>662</u>	DK 35A DIN-Rail mounting kit
<u>663</u>	5-pin Terminal block adapter to DB9 female
<u>6061</u>	RJ45 adapter to DB9 female
<u>661</u>	Serial Null-Modem adapter 9PF-9PF, change male to female

[>Back to top](#)

■ Packaging

Packing list	<ul style="list-style-type: none">• USB-COM Plus Mini device• USB 2.0 High-Speed cable• 4 rubber feet for table mode
---------------------	--

[>Back to top](#)



USB-COM Plus Configurator

[>Back](#)

VScom USB-COM Plus Configurator

File Help

Present COM-Ports Show disconnected devices

COM3
COM4
COM6

Port Settings

Min. Read Timeout (ms): Serial Enumerator

Min. Write Timeout (ms): Serial Printer

Polling Period: Cancel If Power Off

Latency Timer: Event On Surprise Removal

Set RTS On Close

Disable Modem Ctrl At Startup

Default Settings

Optimize for USB-COM

Optimize for USB-CAN

Baud Rate Mappings

Buffered Writes

Rename COM Port

Global Settings

Ignore Hardware Serial Number

Reload Driver

Refresh OK Cancel Apply

Close All Ports VScom USB-COM 232, SN: DN6NP3AA, ID: 4036015, LocalID: 31; Open COM Ports: 0

Terminal Block Adapter

[>Back](#)

